

Cautions:

- For use with AA and AAA size NiMH batteries ONLY! Use with other type batteries voids warranty, may cause damage to the charger/ battery and possibly cause injury to the user.
- Do not leave any battery cell connected to the charger for prolonged periods. Remove the battery promptly after charge is complete.
- Unplug the charger when not in use.
- Do not use, place or store the charger where it may come into contact with water or moisture.
- Always replace frayed or damaged wire and broken plugs immediately.
- Use this charger with the power adapters included in the package only.
- No user serviceable parts, opening chassis will void warranty.
- Charger needs proper ventilation. Make sure charger vents are not being blocked and there is no problem with circulation
- Charge only NiMH batteries on this charger.
- Batteries are not charged as shipped. Must be charged prior to first use.
- Batteries may leak or explode causing personal injury if inserted improperly, disposed of in fire, mixed with other battery types, or short circuit.

Specifications:

- | | |
|--------------------------|-----------------------|
| ● AC Adapter | 100-240VAC, 50 / 60HZ |
| ● Power Input | 12VDC @ 2A |
| ● Charger Current AA | 2.0A±10%, |
| ● Charger Current AAA | 1.2A±10% |
| ● Trickle Current | 150mA |
| ● Operating Temperature: | 0°C – 30°C |

4

Flexible power input allows you to use the 1 hour Charger from home or overseas with its 100V-240V AC Universal Power Supply, or on the road using the included 12V DC Cigarette Lighter Adapter.

Charging Your Batteries

Plug-in either the AC Adapter or the DC Cigarette Lighter Power adapter, and connect the other end of the power adapter cable to the power input jack on the end of the Charger AA/AAA speed charger unit.

Insert any 1 to 4 AA and/or AAA NiMH rechargeable battery cells to be charged into any of the 4 charging locations on the charger unit, observing the direction of the battery as indicated by the diagrams. Only one AA or AAA size NiMH battery cell may be installed into any single charging.

The LED Indicators

Once the battery has been inserted into the Charger, the LED above it will indicate the status of the battery being charged.

LED On- The battery at that location is being "Speed charged". Once the LED turns off, the battery at that location has completed "Speed charging" and is trickle charged for the next 1-2 hours. The cell is now ready for use, but may be left in the charger during the trickle charge to achieve a completely full charge.

LED Flashing- If an indicator LED is flashing above one or more of the cells being charged, this is an indication of an ERROR condition. The battery below the flashing LED is either faulty or at the end of its life and should be replaced, as it is no longer useable.

LED does not turn on – If the LED will not come on after a cell is

2



KD-SCAM-S01

1 Hour Charger Manual

For AA & AAA Size NiMH Batteries

Please Read The Information And Follow All Instructions Thoroughly Before Using This Product

Introduction

This KD-SCAM-S01 1 hour Charger is a highly advanced and fully automatic battery charger which is compatible with all AA and AAA size NiMH batteries commonly used in today's digital camera, MP3, CD players, 2-way radios, radio controlled cars, motorized toys and other electronic devices.

The 1 hour Charger features microprocessor controlled to charge your battery up to 7 times faster than other standard chargers. Not only will it charge the battery safely and reliably, it will prolong battery life. The Charger will not overheat the batteries and damage them. The 1 hour Charger actually prolongs battery life. 1 to 4 batteries can be charged at a time, each with a dedicated LED indicator to show the charge status of that cell.

1

inserted at that location, the voltage of that battery has dropped to a very unhealthy low level. The battery should be replaced.

Notes:

- This 1 hour Charger is designed for use with NiMH (nickel Metal-Hydride) AA and AAA cells only. Do not charge NiCd (Nickel Cadmium) or any type of cells other than NiMH in this charger.
- It is normal for the charger, AC adapter, or the battery cells to become warm during charging.
- Do not install an AAA cell or an AA cell into any one charging location at the same time.
- Batteries will self discharge when not in use. Batteries can be kept fresh if you recharge them every 2-3 months.

Approximate Charge time*

| | |
|------------|------------|
| 800mAh AAA | 65 minutes |
| 1800mAh AA | 60 minutes |
| 2000mAh AA | 75 minutes |

- *Actual charge time will vary depending on the cell's discharge level, capacity and condition. Longer charge time will occur when this charger is used in temperatures above 28°C.

Trouble Shooting Tips:

- Batteries should be replaced when run time becomes short.
- If the LED status indicator does not light up when the charger unit is properly plugged into a power source, and a discharged battery is correctly installed, make sure that the AC socket or cigarette lighter has power and that the battery cell is not defective.
- Use a clean dry cloth when necessary to keep the metal contacts of both charger and battery clean.

3